

Voice Forms Pre-Installation Checklist

Document #: 215

Last Update: 04/27/2010

Page: 1 of 2

Overview

This document outlines the necessary requirements for installation of the Voice Forms application on the Mutare Communication Server (MCS).

Document *145-MCS Specifications*, should be reviewed before attempting to complete this document. We recommend downloading the most recent version from <http://www.mutare.com/techdocs.asp>.

Site Information

Site Name

PBX Particulars

PBX Make/Model:

ISDN PRI Only

T1s should be configured as ISDN PRI only. T1 circuits are connected to the cards on the back of the server via RJ48C jacks. Mutare recommends the following specifications when ordering or configuring phone lines:

- ISDN PRI Trunks, configured 23B+D, NI-2 protocol.
- 2-way, with Called Party Number.
- NOTE: There **must** be a CSU/DSU between the T1 termination (either at the DMARC from the CO or from the PBX) and the MCS. Some PBX cards do not need a CSU/DSU. Consult with your Mutare technician.
- Configure the hunting as ascending (straight-line).

Complete?

Analog Only

Setup a hunt group for incoming calls. It is recommended that this be an ascending (straight-line) hunt group.

Complete?

The Voice Forms application answers inbound calls. A DID should be assigned that routes to the Voice Forms application.

Note: The first question is always the Voice Forms number. Call vectoring/converse step can be used to drop the caller into a particular voice form.

DID for Inbound Calls:

How will individual Voice Forms be accessed by callers? Vectoring? DNIS digits? Will the caller need to enter the Voice Forms number, followed by the pound key?

Voice Forms Pre-Installation Checklist

Document #: 215

Last Update: 04/27/2010

Page: 2 of 2

Server Configuration Information	
Application Server IP Address.	
A local administrator account must be created for services to run under. This account will also be used by Mutare to login to the server. This account may be part of a domain, but this is not necessary.	Username: _____ Password: _____ Domain: _____
Ensure that World Wide Web Server on the Application Server has been installed. ¹	Complete? <input type="checkbox"/>
Ensure that SMTP Virtual Server on the Application Server has been installed. ²	Complete? <input type="checkbox"/>
Corporate SMTP Server (IP address or Host Name). Emails will relay through this server.	
It is recommended that a DNS entry be created for the website. Provide the URL to the ENS website. e.g. http://voiceforms.organization.com	

¹ Mutare will create a new folder for the Web scripts and make it the default. Users will access the website by entering the IP address or host name of the Application Server. The *Active Server Pages* and *Server Side Includes* web service extensions will be enabled for the Voice Forms website. For more information, see Mutare document *130-Web Server*.

² The Voice Forms application has an option to send email through an SMTP server. After installation, Mutare Software will configure the SMTP Virtual Server to use your existing SMTP server as a "smart host". This will allow the Application Server to relay messages through your existing SMTP server. Your existing SMTP server must be configured to allow relaying. If an SMTP server does not exist, one must be established before using EVM Plus. For more information, see Mutare document *129-SMTP Server*.